

INT-R

MULTIFUNCTION EXPANDER FOR CARD / CHIP READERS

Extension module for INTEGRA control panels enabling proximity card readers and/or iButton chip readers to be connected to implement access control to and arming/disarming of the partition. The INT-R expander can interface with the INTEGRA and CA-64 alarm control panels.

FEATURES

- support for two proximity card / iButton chip readers
- compatible with Wiegand 26 format readers
- relay to control electromagnetic door lock
- input for door status control
- input for door opening with a button
- capability to automatically open the door in case of fire alarm
- tamper input



TECHNICAL SPECIFICATION

| | |
|---|-------------------|
| Supply voltage | 12 V DC \pm 15% |
| Standby current consumption | 110 mA |
| Maximum current consumption | 150 mA |
| Relay contacts rating (resistive load) | 5 A / 30 V DC |
| Environmental class | II |
| Operating temperature range | -10°C...+55°C |
| Maximum humidity | 93 \pm 3% |
| Dimensions | 140 x 68 mm |
| Weight | 80 g |